


FB2 Material


FB2 is a high saturation Manganese-Zinc ferrite designed for high flux power applications. The losses are optimized for the 60°–100°C range because most of the transformers of this type are designed to run hot where efficiency levels are highest. The frequency range for this material is between 10 kHz and 200 kHz. FB2 is available in a wide variety of shapes including toroids, slugs, bobbins, and cup and tack assemblies.

Parameter	Symbol	Unit	Standard Test Conditions		Value
Initial Permeability	μ_i	—	10 kHz ~ 0.1mT		2000 ± 20%
Amplitude Permeability	μ_a	—	400mT 320mT	25°C 100°C	2400 1825
Saturation Flux Density	B_{sat}	mT	$H=796A/m = 10$ Oe @ 25°C @100°C		470 350
Residual Flux Density	B_r	mT	$H \rightarrow 0$ (from near saturation) 10kHz	25°C	200
Coercive force	H_c	A/m	$B \rightarrow 0$ (from near saturation) 10kHz	25°C	21
Relative Loss Factor	$\tan \delta / \mu_i$		100 kHz ~ 0.1mT		30×10^{-6}
Curie Temperature	T_c	°C	$B < 0.1$ mT 10kHz		200
Total Power Loss Density	P_v	mW/cc	200mT 200mT 200mT 200mT 200mT	16kHz 16kHz 16kHz 25kHz 25kHz	120 110 110 190 190
Volume Resistivity	ρ	Ω-cm	1V/cm 25°C		100


Dynamic Magnetization (BH) Loop




Initial Permeability vs. Temperature




Power Loss Density vs. Temperature




Power Loss Density vs. Frequency



Complex Permeability vs. Frequency



Static Magnetization: Permeability vs. B



Relative Loss Factor vs. Frequency

